



NERO XA3200 Amplifier

OSD Audio's NERO XA3200 3-channel Class H amplifier supplies 260 Watts per channel of clean power for exceptional sound quality in a home theater surround sound speakers setup. Includes balanced and unbalanced gold and gun-metal plated connectors, brushed metal finish, and front panel status indicators. Our NERO XA3200 is a Class H amplifier that combines the benefits of Class A/B in a more efficient package. Class H amplifiers are a variation of Class A/B amps but include high voltage and low voltage rails to modulate power consumption.

SPECIFICATIONS

- 3 Channel Class H
- Power Output:
 - 165W per channel 8ohms
 - 260W per channel 4ohms
- Inputs: XLR/RCA
- 12V Trigger
- Frequency Response: 7.5Hz to 20kHz +/-3dB
- Input Sensitivity: 1 Volt
- Power: 120/220VAC, $\pm 3\%$, 50Hz - 60Hz
- Dimensions: H 6 x W 17 x D 16.75 in.
- Weight: 48 lbs